Product family datasheet



HSR

Metal halide lamps



Areas of application

- Entertainment
- Architainment

Product family benefits

- Outer bulb for ease of handling

Product family features

- Single-ended lamps similar to HTI lamps







Product family datasheet

Technical data

	Electrical d	Electrical data		Photometrical data			Dimensions & weight	
Product description	Nominal voltage	Nominal current	Nominal luminous flux	Luminance	Color temper- ature	Diameter	Length	
HSR 400 W/60	670 V	69 A	33000 lm	20000 cd/cm ²	6000 K	230 mm	1100 mm	
HSR 575 W/60	950 V	7 A		10000 cd/cm ²	6000 K	300 mm	1250 mm	
HSR 575 W/72	975 V	700 A	49000 lm	10000 cd/cm ²	7200 K	300 mm	1250 mm	

		Lifespan	Additional product data	Capabilities	Environmental information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)
Product description	Light center length (LCL)	Lifespan	Base (standard designation)	Burning position	Date of Declaration
HSR 400 W/60	62.0 mm	1000 h	GX9.5	Other	05-03-2024
HSR 575 W/60	65.0 mm	1000 h	GX9.5	Other	05-03-2024
HSR 575 W/72	65.0 mm	1000 h	GX9.5	Other	05-03-2024

Product description	Primary Article Identifier	Candidate List Substance 1	Declaration No. in SCIP database
HSR 400 W/60	4050300315942 4008321631503	No declarable substances contained	In work
HSR 575 W/60	4050300941776 4008321625885	No declarable substances contained	In work
HSR 575 W/72	4008321074126 4008321625908 4008321662583	No declarable substances contained	No declarable substances contained

Product family datasheet

Safety advice

Because of their high luminance, UV radiation and high internal pressure during operation, HSR lamps may only be operated in enclosed lamp casings specially constructed for the purpose. Appropriate filters must ensure that UV radiation is reduced to an acceptable level. Mercury is released if the lamp breaks. Special safety precautions must be taken. Information on safety and handling is available on request or can be found in the leaflet included with the lamp or in the operating instructions. HSR lamps are not capable of hot restarts.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.