OSRAM

ORIGINAL - PLASTIC MF BASE -

Original spare part





The cost-effective original spare parts

Discover our ORIGINAL signal lamps for printed circuit boards. These lamps with OSRAM's reliable OEM quality feature a wide product range and can be used for instrument and switch lighting.

Technical data

Product information

Order reference	2351MFX6
Application (Category and Product specific)	Auxiliary lamp


Electrical data

Power input	1.32 W
Nominal voltage	12.0 V
Nominal wattage	1.20 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometrical data

Luminous flux	7.5 lm
Luminous flux tolerance	±20 %

Dimensions & weight



Diameter	5 mm
Product weight	0.77 g
Length	17.5 mm

Colors & materials

Base color Jet black

Lifespan

Lifespan B3	600 h
Lifespan Tc	3000 h

Additional product data

Base (standard designation)	BX8.4d
-----------------------------	--------

Capabilities

Thickness of PCB	1.25 mm
Technology	AUX

Certificates & standards

ECE category	
Approval marks – approval	-

Country specific categorizations

Order reference	2351MFX6

Environmental information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)			
Date of Declaration	05-03-2024		
Primary Article Identifier	4008321011756 4008321096852 4062172046916		
Candidate List Substance 1	No declarable substances contained		
Declaration No. in SCIP database	In work		

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4062172046916	ORIGINAL - PLASTIC MF BASE 2351MFX6	Unpacked 1	- x - x -		
4062172046923	ORIGINAL - PLASTIC MF BASE 2351MFX6	Folding carton box 10	- x - x -		
4062172046930	ORIGINAL - PLASTIC MF BASE 2351MFX6	Shipping carton box 50	148 mm x 115 mm x 55 mm	0.94 dm³	123.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.













OSRAM