

Lamps with metal bases -

Original spare part



The cost-effective original spare parts

ORIGINAL signal lamps with metal bases feature - like all ORIGINAL products from OSRAM - a reliable OEM quality. Due to the wide product range, the lamps can be used as original spare lamps for different applications.



Technical data

Product information

Order reference	3894
Application (Category and Product specific)	Auxiliary lamp

Electrical data

Power input	3 W
Nominal voltage	12.0 V
Nominal wattage	3.00 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometrical data

Luminous flux	22 lm
Luminous flux tolerance	±20 %

Dimensions & weight

Diameter	9 mm
Product weight	1.87 g
Length	23.9 mm

Lifespan

Lifespan B3	1000 h
Lifespan Tc	2000 h

Additional product data

Base (standard designation)	BA9s
-----------------------------	------

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	-
Approval marks – approval	-

Country specific categorizations

Order reference	3894
-----------------	------

Product datasheet

Environmental information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of Declaration	05-03-2024
Primary Article Identifier	4008321095725
Declaration No. in SCIP database	In work

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321095725	OSRA3894	-	-	-
4008321095732	OSRA3894	-	-	-
4008321095725	OSRA3894	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095725	ORIGINAL - METAL BASE 3894	Unpacked 1	- x - x -		
4008321095732	ORIGINAL - METAL BASE 3894	Folding carton box 10	46 mm x 29 mm x 112 mm	0.15 dm³	29.70 g
4008321095749	ORIGINAL - METAL BASE 3894	Shipping carton box 50	148 mm x 115 mm x 55 mm	0.94 dm³	178.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

