

# ORIGINAL - PLASTIC MF BASE -

Original spare part



## The cost-effective original spare parts

Discover our ORIGINAL signal lamps for printed circuit boards. These lamps with OSRAM's reliable OEM quality feature a wide product range and can be used for instrument and switch lighting.



# Product datasheet

## Technical data

### Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

### General Product Information

Global order reference	2722MFX
------------------------	---------

### Electrical Data

Power input	2 W
Nominal voltage	12.0 V
Nominal wattage	2 W
Test voltage	13.5 V
Power input tolerance	±10 %

### Photometric Data

Nominal luminous flux	10.2 lm
Luminous flux tolerance	±25 %

### Physical Attributes & Dimensions

Diameter	5 mm
Product weight	1.18 g
Length	23.5 mm
Lamp base	BX8.5d

### Colors & materials

Base color	Pale green
------------	------------

### Lifetime Data

Lifespan B3	1300 hr
Lifespan Tc	4000 hr

### Capabilities

Thickness of PCB	1.25 mm
Technology	AUX

### Certificates & standards

ECE category	-
Approval marks – approval	-

## Product datasheet

### Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	12-09-2024
Primary article identifier	4008321297181
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

### Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321297181	OSRA2722MFX	-	-	-

### Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321297181	ORIGINAL - PLASTIC MF BASE 2722MFX	Unpacked 1	- x - x -		
4008321297204	ORIGINAL - PLASTIC MF BASE 2722MFX	Shipping carton box 50	148 mm x 115 mm x 55 mm	0.94 dm <sup>3</sup>	144.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### Application advice

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



# OSRAM